

Dual High with Trays FCB100T



## **Features**

- Two hot swappable converters in 1U
- Cost effective solution
- Full range of block and agile converters
- Meets or exceeds IESS 308/309 requirements
- High linearity
- Low group delay
- Front panel control (local)
- Full remote control (remote)

## Overview

The Advantech Dual - HP range of converters uses the latest technology in conversion, giving two independent conversion chains in 1 RU package, local and remote control thus providing the ultimate in performance and user friendly operation at a very competitive price.

The spectral purity, low phase noise and stability exceed the requirements of all major international satellite network operators.

The flexible and comprehensive monitor and control features on the HP converter ensure that it will fit into any network management system architecture. The user-friendly front panel or the RS485 remote interface will provide full set-up and fault monitoring facilities. The RS232 will provide the Monitor and Control functions via a PC and will also allow for software downloading.

The converter uses a PLL oscillator either locked to a highly stable internal 10 MHz reference or if the external reference option is fitted and the proper level of signal is present, the PLL oscillator will automatically lock to the external reference.

# **Application**

The HP range of converters is particularly suited for use in VSAT, SCPC Networks, SNG, DVB-RCS and Hub systems were compact redundancy is required. This makes them an ideal choice for large earth stations requiring cost effective solutions for frequency conversion. The lightweight, rugged and compact design also ensures that the HP converter provides the ideal solution for mobile truck or flyaway DSNG systems. With fully welded aluminum chassis and robust modular internal construction the converter can even meet the demands of military installations. The HP range of converters provides an industry leading MTBF of over 120,000 hours.


# **Operating Bands**

## **Up-Converters**

Model Number	RF Output	IF Frequency			
ARUD-LCT	5.850 - 6.425 GHz Non-inverted	950-1525 MHz			
ARUD-LCXT	5.850 - 6.725 GHz Non-inverted	950-1825 MHz			

### **Down-Converters**

201111011010				
Model Number	RF Input	IF Frequency		
ARED-CXLT	3.40 - 4.20 GHz	950 – 1750 MHz Inverted		
ARDD-CXLT	3.40 - 4.20 GHz	950 - 1750 MHz (non-inverted)		





# **C-Band Block Frequency Converters**

Up-Converter		Down-Converter	
F Input		RF Input	
Frequency range	(See table on front page)	Frequency range	(See table on front page)
Impedance	50 Ω	Impedance	50 Ω
Input Connector	SMA (female)	Input Connector	SMA (female)
Return loss	16 dB	Return loss	18 dB
F Output		IF Output	
Output power (P1dB)	0 dBm	Frequency range	(See table on front page)
Frequency range	(See table on front page)	Output level	+5 dBm at P1dB
IMD3 (two tone)	-40 dBc max @ -10 dBm output	Output Connector	sMA female
Output connector	SMA (female)	Connector Impedance	50 Ω
Connector Impedance	50 Ω	Return Loss	16 dB
Return loss	18 dB		
ransfer Characteristics		Transfer Characteristic	S .
Conversion Gain	20 dB @ max gain setting	Conversion Gain	40 dB @ max gain setting
Gain adjustment	20 dB	Gain adjustment	20 dB
Attenuator step size	0.1 dB	Attenuator step size	0.1 dB
Gain flatness	±1.5 dB p-p over 575 MHz 1.0 dB p-p over 40 MHz	Gain flatness	±2.0 dB p-p over 800 MHz (NINV Down Converters)+ 1.0 dB p-p over 40 MHz
Gain stability	±0.25 dB max. /24 hours ±1 dB over temp. range	Gain stability	±0.25 dB max. / 24 hours ±1 dB over temp. range
Spurious	-55 dBc carrier related @ -10 dBm < -60 dBm non-carrier related	Spurious	-55 dBc @ -10 dBm
Phase noise	Meets or Exceeds IESS 308/309	Image rejection	60 dB
		Noise Figure	20 dB
		Phase noise	Meets or Exceeds IESS 308/30
Reference		Mechanical	
External Reference	10 MHz, +/- 3 dBm input level		Width 19" (482.6 mm)
Internal reference stability	± 2 x 10 <sup>-10</sup> / day	Dimensions	Height 1U 1.75" (44.5 mm)
Aging	± 5 x 10 <sup>-8</sup> / year	_ Dimensions	Depth 24" (609.6 mm)
Environmental		Power Supply	
Operational	0°C to +50°C standard	Voltage	90 – 265 VAC (47 – 63 Hz)
Storage	-55°C to +85°C	Power	50W (typical)
Humidity	Non-condensing	Connector	IEC 603320 10A
Altitude	3,000m AMSL		
		Monitor and Control	
		RS 485	DB9
		RS 232	DB9
		Discrete	DB9
		Ethernet (optional)	RJ45 F

# NORTH AMERICA USA

Tel: +1 703 659 9796 Fax: +1 703 635 2212 info.usa@advantechwireless.com

### CANADA

Tel: +1 514 420 0045 Fax: +1 514 420 0073 info.canada@advantechwireless.com

### EUROPE UNITED KINGDOM

Tel: +44 1480 357 600 Fax: +44 1480 357 601 info.uk@advantechwireless.com

### RUSSIA & CIS

Tel: +7 495 971 59 18 info.russia@advantechwireless.com

### INDIA

Tel: +91 33 2415 5922 info.india@advantechwireless.com

## SOUTH AMERICA

Tel: +1 514 420 0045 Fax: +1 514 420 0073 info.latam@advantechwireless.com

## BRAZIL

Tel: +55 11 3054 5701 Fax: +55 11 3054 5701 info.brazil@advantechwireless.com An ISO 9001: 2008 Company



Ref.: PB-FCB100T-C-13150